


INTERNATIONAL APPLICATION PUBLISHED UNDER THE PATENT COOPERATION TREATY (PCT)

(51) International Patent Classification ⁷ : H03M 13/27		A1	(11) International Publication Number: WO 00/60750
			(43) International Publication Date: 12 October 2000 (12.10.00)
(21) International Application Number: PCT/KR00/00300		(81) Designated States: AU, BR, CA, CN, IN, JP, RU, European patent (AT, BE, CH, CY, DE, DK, ES, FI, FR, GB, GR, IE, IT, LU, MC, NL, PT, SE).	
(22) International Filing Date: 3 April 2000 (03.04.00)			
(30) Priority Data:		Published	
1999/12858	2 April 1999 (02.04.99)	KR	With international search report.
1999/11798	6 April 1999 (06.04.99)	KR	
(71) Applicant: SAMSUNG ELECTRONICS CO., LTD. [KR/KR]; 416, Maetan-dong, Paldal-gu, Suwon-shi, Kyungki-do 442-370 (KR).			
(72) Inventors: KIM, Min-Goo; 973-3, Youngtong-dong, Paltal-gu, Suwon-shi, Kyonggi-do 442-470 (KR). KIM, Beong-Jo; Mujigaemaoul #201, Kumi-dong, Puntang-gu Songnam-shi, Kyonggi-do 463-500 (KR). LEE, Young-Hwan; 237-7, Chongja-dong, Puntang-gu, Songnam-shi, Kyonggi-do 463-010 (KR).			
(74) Agent: LEE, Keon-Joo; Mihwa Bldg. 110-2, Myon- gryun-dong 4-ga, Chongro-gu, Seoul 110-524 (KR).			

(54) Title: INTERLEAVING / DEINTERLEAVING APPARATUS AND METHOD FOR A COMMUNICATION SYSTEM



(57) Abstract

A device for generating L addresses, which are smaller in number than $2^m \times N_g$ virtual addresses, for reading data from an interleaver memory in which L data bits are stored, the device including: N_g PN generators each including m memories; an address generator for adding an offset value to the input data size to provide a virtual address having a size of a multiple of 2^m , and generating addresses other than addresses corresponding to the offset value in address generation areas using the address generation areas having the size of 2^m ; and means for reading the input data from the interleaver memory using the addresses generated from the address generation areas.

FOR THE PURPOSES OF INFORMATION ONLY

Codes used to identify States party to the PCT on the front pages of pamphlets publishing international applications under the PCT.

AL	Albania	ES	Spain	LS	Lesotho	SI	Slovenia
AM	Armenia	FI	Finland	LT	Lithuania	SK	Slovakia
AT	Austria	FR	France	LU	Luxembourg	SN	Senegal
AU	Australia	GA	Gabon	LV	Latvia	SZ	Swaziland
AZ	Azerbaijan	GB	United Kingdom	MC	Monaco	TD	Chad
BA	Bosnia and Herzegovina	GE	Georgia	MD	Republic of Moldova	TG	Togo
BB	Barbados	GH	Ghana	MG	Madagascar	TJ	Tajikistan
BE	Belgium	GN	Guinea	MK	The former Yugoslav Republic of Macedonia	TM	Turkmenistan
BF	Burkina Faso	GR	Greece	ML	Mali	TR	Turkey
BG	Bulgaria	HU	Hungary	MN	Mongolia	TT	Trinidad and Tobago
BJ	Benin	IE	Ireland	MR	Mauritania	UA	Ukraine
BR	Brazil	IL	Israel	MW	Malawi	UG	Uganda
BY	Belarus	IS	Iceland	MX	Mexico	US	United States of America
CA	Canada	IT	Italy	NE	Niger	UZ	Uzbekistan
CF	Central African Republic	JP	Japan	NL	Netherlands	VN	Viet Nam
CG	Congo	KE	Kenya	NO	Norway	YU	Yugoslavia
CH	Switzerland	KG	Kyrgyzstan	NZ	New Zealand	ZW	Zimbabwe
CI	Côte d'Ivoire	KP	Democratic People's Republic of Korea	PL	Poland		
CM	Cameroon	KR	Republic of Korea	PT	Portugal		
CN	China	KZ	Kazakistan	RO	Romania		
CU	Cuba	LC	Saint Lucia	RU	Russian Federation		
CZ	Czech Republic	LI	Liechtenstein	SD	Sudan		
DE	Germany	LK	Sri Lanka	SE	Sweden		
DK	Denmark	LR	Liberia	SG	Singapore		
EE	Estonia						

INTERLEAVING/DEINTERLEAVING APPARATUS AND METHOD FOR A COMMUNICATION SYSTEM

5 BACKGROUND OF THE INVENTION

1. Field of the Invention

10 The present invention relates generally to an interleaving/deinterleaving device and method, and in particular, to an interleaving/deinterleaving device and method for a turbo encoder used in radio communication systems such as satellite, ISDN (Integrated Services Digital Network), digital cellular, W-CDMA (Wideband Code Division Multiple Access), IMT-2000 and W-ATM (Wideband Asynchronous Transfer Mode) communication systems.

15 2. Description of the Related Art

20 A turbo code is a type of an error correction code which affects the reliability of a digital communication system. An existing turbo coder is divided into a serial turbo coder and a parallel turbo coder. A parallel turbo encoder encodes an input frame of L information bit streams into parity symbols using two simple parallel concatenated codes, wherein recursive systematic convolutional (RSC) encoders are typically used for component encoders. In addition, the parallel turbo encoder includes an interleaver connected between the component encoders.

25 In the turbo encoder, interleaving is performed to randomize data streams which are input from the component encoders on a frame unit basis and to improve the distance property of a codeword. In particular, it is expected that the turbo encoder will be used in a Supplemental Channel (or traffic channel) of an IMT-2000 (or CDMA-2000) communication system and in a data channel of UMTS (Universal Mobile Telecommunication System) proposed by ETSI (European Telecommunication Standards Institute). Thus, a method for
30 employing an interleaver with a turbo encoder for this purpose is required.

35 FIG. 1 shows a common parallel turbo encoder, which is disclosed in detail in US patent No. 5,446,474, issued on August 29, 1995, which is hereby incorporated by reference.

Referring to FIG. 1, the turbo encoder includes a first component encoder 111 for encoding input frame data, an interleaver 112 for interleaving the input frame data, and a second component encoder 113 for encoding an output of the interleaver 112. A known RSC

- 2 -

encoder or NSC (Non-Recursive Systematic Convolutional) encoder is typically used for the first and second component encoders 111 and 113. Such component encoders have different structure according to a coding rate, a constraint length K and a generator polynomial. Further, the interleaver 112 has the same size as the input information bit frame, and rearranges the sequence of the information bits provided to the second component encoder 113 to reduce the correlation between the information bits.

For the internal interleaver (or a turbo interleaver) 112 of the turbo encoder, various interleavers are proposed, such as PN (Pseudo Noise) random interleaver, random interleaver, block interleaver, non-linear interleaver, and S-random interleaver. However, so far, such interleavers are mere algorithms designed to improve their performances in terms of scientific theory rather than practice. When implementing an actual system, the hardware implementation complexity must be taken into consideration. A description will now be made of properties and problems associated with the conventional interleaver for the turbo encoder.

Performance of the turbo encoder is dependent upon the internal interleaver. In general, an increase in the input frame size (i.e., the number of information bits included in one frame) requires an increase in performance of the turbo encoder. However, an increase in interleaver size requires a geometric increase in calculations. Therefore, in general, it is not practical to implement the interleaver for a large frame size.

Generally speaking according to experiments, the random interleaver is superior in performance to the block interleaver. However, the random interleaver is disadvantageous in that an increase in the variety and size of the frame causes an increase in the required memory capacity for storing an interleaver index (i.e., mapping rule or address). That is, the memory capacity required for addressing greatly increases. Therefore, taking the required hardware size into consideration, it is preferable to employ an address enumeration method for reading data stored at a corresponding address by generating an address at every symbol clock using an index generating rule rather than a look-up table method for storing the interleaver index.

In conclusion, when various interleaver sizes are required and the hardware implementation complexity is limited, as in an IMT-2000 or UTMS system, the turbo interleaver should be designed to guarantee optimal interleaver performance by taking inherent limitations into consideration. That is, an interleaver which performs interleaving/deinterleaving according to a specific interleaving rule is required. In addition, the turbo interleaver requires good interleaver properties (e.g., distance property, weight

property and random property).

A IMT-2000 or UMTS specification has not yet been given which provides any definition for the turbo interleaver. The forward link and the reverse link defined by the IMT-2000 specification have various types of logical channels and various interleaver sizes. Therefore, in order to meet this variety requirement, an increase in the memory capacity is required. For example, in a CDMA-2000 forward link transmission mode, the interleaver size can vary from 144 bits/frame to 36864 bits/frame.

To sum up, the prior art has the following disadvantages.

First, for the conventional internal interleaver of the turbo encoder, PN random interleavers, random interleavers, block interleavers, non-linear interleavers, and S-random interleavers may be used. However, such interleavers are mere algorithms designed to improve their performances in terms of scientific theory rather than practice. Therefore, when implementing an actual system, the hardware implementation complexity of such interleavers must be considered. However, this is not specifically defined.

Second, since a controller (CPU or host) of the transceiver must store interleaving rules according to the respective interleaver sizes in the existing interleaving method using a look-up table, a host memory requires a separate capacity in addition to an interleaver buffer. That is, when the frame size is varied, and increases in size, an increased memory capacity for storing the interleaver index (i.e., mapping rule or address) is required.

Third, it is not easy to implement an interleaver satisfying both the distance property and the random property.

SUMMARY OF THE INVENTION

It is, therefore, an object of the present invention to provide an interleaving/deinterleaving device and method which satisfies distance property, weight property and random property of a turbo encoder in a communication system.

It is another object of the present invention to provide a device and method for performing interleaving using a virtual address area having a size $2^m \times N$ determined by adding a specific value to an input data size in a communication system.

It is yet another object of the present invention to provide an interleaving device and

- 4 -

method which prevents generation of invalid addresses caused by a specific value added to an input data size to perform interleaving.

It is yet another object of the present invention to provide a method for determining an optimal initial value of a PN sequence generator which generates a random address component according to an address area of an internal interleaver in a turbo encoder.

To achieve the above object, there is provided a device for generating L addresses, which are smaller in number than $2^m \times N_g$ virtual addresses, for reading data from an interleaver memory in which L data bits are stored. The device comprises a selection circuit including N_g PN (Pseudo Noise) generators each including m memories, wherein one of the PN generators generates (OSV-1) offset values (OSV) satisfying $OSV = 2^m \times N_g - L$ and $(2^m - OSV)$ non-zero states in response to a first clock signal and the other PN generators each generate $(2^m - 1)$ non-zero states, wherein the selection circuit selects the PN generators according to a predetermined order in response to a select signal and outputs a state generated from the selected PN generator; means for detecting each offset state from one PN generator, providing said select signal for not selecting said one PN generator so that the detected offset state is not output, and generating high address bits related to each selection of the PN generators in response to clock pulses of a second clock signal having a shorter period than the first clock signal; means for generating low address bits determined by subtracting one from each state output from the selection circuit when a number of selection periods of the PN generators is smaller than 2^m , and generating low address bits corresponding to $2^m - 1$ when the number of selection periods is 2^m ; and an address buffer for storing the addresses, said L addresses each being comprised of the high address bits and the low address bits.

BRIEF DESCRIPTION OF THE DRAWINGS

The above and other objects, features and advantages of the present invention will become more apparent from the following detailed description when taken in conjunction with the accompanying drawings in which:

FIG. 1 is a block diagram illustrating a conventional turbo encoder;

FIG. 2 is a block diagram illustrating an interleaving device in a communication system according to an embodiment of the present invention;

FIG. 3 is a block diagram illustrating a deinterleaving device in a communication system according to an embodiment of the present invention;

FIG. 4 is a diagram illustrating that the data bits interleaved according to an offset value exist between interleaved data bits, when interleaving is performed using a virtual address area determined by adding the offset value to the input data size;

- 5 -

FIG. 5 is a diagram illustrating that the output data bits are connected after deleting the invalid data bits of FIG. 4;

FIG. 6 is a diagram illustrating a PN generator having a generator polynomial of $(1+x+x^6)$;

FIG. 7 is a block diagram further illustrating the interleaving device of FIG. 2 according to a first embodiment of the present invention;

FIG. 8 is a detailed block diagram of the address generator shown in FIG. 7;

FIG. 9 is a flow chart illustrating a procedure for generating an interleaving address according to a first embodiment of the present invention;

FIG. 10 is a block diagram illustrating an interleaving device according to a second embodiment of the present invention;

FIG. 11 is a timing diagram of the interleaving device of FIG. 10;

FIG. 12 is a diagram illustrating how to detect an offset value in the last PN generator;

FIG. 13 is a flow chart illustrating a procedure for generating an interleaving address according to a second embodiment of the present invention; and

FIG. 14 is a flow chart illustrating a procedure for calculating an optimal initial state value (or seed) of the PN generators according to the second embodiment of the present invention.

DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENT

A preferred embodiment of the present invention will be described herein below with reference to the accompanying drawings. In the following description, well-known functions or constructions are not described in detail to avoid obscuring the invention in unnecessary detail.

To design a turbo encoder which has optimal performance with respect to various frame sizes, many parameters must be considered, such as the amount of memory for the component encoders of the turbo encoder (i.e., constraint length K), a plurality of generator polynomials and an optimal code rate. It is very difficult to design a turbo encoder which has optimal performance through experiments it is not verified how such parameters(generator polynomials and an optimal code rate, etc) affect the performance.

Therefore, in general, interleavers are implemented by determining conditions satisfying several given criteria. The criteria are as follows:

Distance Property : The distance between adjacent codeword symbols should be

- 6 -

maintained to a certain extent. Since this has the same function as a codeword distance property of a convolutional code, it is preferable that the interleaver be designed to have a longer distance, if possible.

5 Weight Property : The weight of a codeword corresponding to a non-zero information word should be higher than a threshold value. Since this has the same function as the minimum distance property of the convolutional code, it is preferable that the interleaver should be designed to have a greater weight, if possible.

10 Random Property : The correlation factor between output word symbols after interleaving should be much lower than the correlation factor between original input word symbols before interleaving. That is, randomization between the output word symbols should be completely performed. This makes a direct effect on the quality of extrinsic information generated in continuous decoding.

15 A description of the invention will now be described hereinbelow with reference to the accompanying drawings.

20 The invention proposes an optimal interleaving/deinterleaving device satisfying properties (including distance property, weight property and random property) of the turbo interleaver.

25 Generally, in the turbo encoder, a random interleaver has good performance, especially with larger frame sizes. It is therefore preferable to design an interleaver such that the complexity is decreased while incorporating the performance of a random interleaver. To this end, an embodiment of the present invention employs a linear feedback shift register (LFSR) for generating a PN sequence and uses a random number generated therefrom as an address. However, when using this method, the following problems should be considered.

30 First, the PN sequence has a period of $2^m - 1$.

 Second, the turbo code is processed on an input frame size unit basis. However, most frame sizes cannot be expressed in terms of a power of 2.

35 To solve this problem, a proposed address generator for the turbo interleaver adds a minimum value (hereinafter, referred to as an offset value (OSV)) to the frame size L to make a virtual interleaving size $N = L + \text{OSV}$ become a multiple of 2^m , when the size L of the frame data to be interleaved cannot be expressed in terms of a power of 2. Here, the offset value is

added to the frame size such that the number of consecutive '0' bits from the least significant bit (LSB) is at least one when the frame size is converted to a binary value. Then, combinations of a group number N_g and a value 'm' are calculated, which satisfy a virtual frame size N of $N_g \times 2^m$. For the respective combinations, PN addresses are generated according to an area of size 2^m and then selected sequentially or randomly to interleave the whole input frame. Here, the group number N_g and the value 'm' are determined through computer simulation and a search algorithm (described below) to optimally satisfy the interleaver properties.

For example, a description will be made regarding a method for determining the offset value when the frame size is 376 (=101111000). The frame size is converted to a binary value 101111000 (=376), and then an offset value is added to the frame size such that the number of consecutive zero (0) bits from the LSB becomes at least 1. Herein, the offset value can be 8 (=1000), for example. Therefore, the virtual interleaving size (or virtual frame size) is 384. When the interleaving addresses are generated for the virtual interleaving size, additional unnecessary read addresses are generated for each address added by the added offset value. Such unnecessary addresses are called "invalid address". If the offset value is added to the input data size value such that the input frame should be expressed in terms of a power of 2, the virtual interleaving size becomes 512 and the offset value becomes 136. An increase in a size 4600 input frame requires an offset value of 3592 to reach $2^{14} = 8192$, thereby making it difficult to process 3592 invalid addresses. Therefore, a proper offset value is added such that the virtual interleaving size should be $2^m \times N_g$. Further, it is necessary to properly divide the group number N_g . However, an increase in the group number may cause deterioration in the random property of the codewords. In addition, since a great decrease in the group number causes an increase in the area size, the memory capacity for storing the interleaving index (i.e., mapping rule or address) is increased. Therefore, the proper values are determined through simulations.

A turbo interleaver according to the present invention permutes the sequence of the input information bits by offset controlled PN interleaving, and provides the permuted information bits to the second component encoder. Therefore, the interleaver according to the present invention includes an input/output data buffer for storing input information bits, and an offset controlled PN interleaving block (comprised of a partial reversal interleaver plus a comparator) which divides the virtual interleaver size determined by adding the offset value to the input data size into several areas to generate random addresses according to the respective areas, and then sequentially or randomly selects the generated random addresses to generate interleaved addresses. In addition, for the first and second component encoders, the turbo encoder can use not only the conventional component encoder, but also a component

encoder specified by the CDMA-2000 system and a component encoder specified by the UMTS system. Further, the interleaver according to the present invention can be applied to not only an internal interleaver of a serial turbo encoder but also a channel interleaver.

5 The term "area" as used herein refers to each address area when the virtual interleaver size is divided, and the term "group" refers to each address area divided by the invalid addresses generated by the added offset value. In addition, the interleaver according to the present invention is called an offset controlled PN interleaver (OCPNI).

10 FIGS. 2 and 3 show the structure of interleaver and deinterleaver according to the present invention, respectively.

15 With reference to FIG. 2, a description will be made of the interleaver for interleaving the frame data output from the first component encoder. An address generator 211 generates a read address for rearranging the sequence of data bits according to an input frame data size L and an input clock, and provides the generated address to an interleaver memory 212. The interleaver memory 212 sequentially stores the input data in a write mode of operation, and reads the data according to the address provided from the address generator 211 in a read mode of operation. A counter 213 receiving an input clock, provides a write address to the interleaver memory 212. As stated above, the interleaver sequentially stores input data in the interleaver memory 212 in the write mode of operation, and reads the data stored in the interleaver memory 212 according to the read address generated by the address generator 211 in the read mode of operation. Alternatively, the interleaver can store the input data in the interleaver memory 212 after rearranging the sequence of the data bits in the write mode of operation, and sequentially read the data in the read mode of operation.

25 With reference to FIG. 3, a description will be made of the deinterleaver according to an embodiment of the present invention. An address generator 311 generates a write address for restoring the sequence of the input data to the original state according to the input frame data size L and the input clock, and provides the generated write address to a deinterleaver memory 312. The deinterleaver memory 312 stores the input data according to the write address provided from the address generator 311 in the write mode of operation, and sequentially reads the stored data in the read mode of operation. A counter 313 receiving the clock, provides the deinterleaver memory 312 with a read address for reading the data from the deinterleaver memory 312. As stated above, the deinterleaver has the reverse operation of the interleaver but has the same structure as the interleaver. The only difference therebetween is the sequence of the input data bits in the write and read modes. Therefore, a description hereinbelow will be made with reference to only the interleaver.

- 9 -

Now, a description will be made of an interleaving device according to a first embodiment of the present invention. The interleaving device according to the first embodiment of the present invention performs interleaving according to an algorithm shown in Equation 1 below.

```

[Equation 1]
{N=L+OSV;
i=0;
10 /*Find  $N=2^m \times N_g$ */
for(ADDRESS_WRITE=0;ADDRESS_WRITE<= $2^m-2$ ;ADDRESS_WRITE++)
{for(g=0;g<= $N_g-1$ ;g++)
{ADDRESS_READ[i]=[PNg(ADDRESS_WRITE)-1]+g* $2^m$ ;
if(ADDRESS_READ<=L-1){
15 ADDRESS_READ[i]=ADDRESS_READ[i]-
OFFSET(ADDRESS_READ[i],GTH); i++;
}
}
/*Overwrite ADDRESS_READ with the same address as ADDRESS_WRITE*/
20 ADDRESS_WRITE=( $2^m-1$ );
for(g=0;g<= $N_g-1$ ;g++)
{ADDRESS_READ[i]=ADDRESS_WRITE+g* $2^m$ -OFFSET(ADDRESS_WRITE,
GTH); i++;
}
25 }
/*OFFSET Generation Algorithm*/
function OFFSET(ADDRESS_READ,GTH){
if(ADDRESS_READ<GTH[0])OFFSET=0;
else if(GTH[0]<ADDRESS_READ<GTH[1])OFFSET=1;
30 else if(GTH[1]<ADDRESS_READ<GTH[2])OFFSET=2;
else if(GTH[2]<ADDRESS_READ<GTH[3])OFFSET=3;
else if(GTH[3]<ADDRESS_READ<GTH[4])OFFSET=4;
else if(GTH[4]<ADDRESS_READ<GTH[5])OFFSET=5;
else if(GTH[5]<ADDRESS_READ<GTH[6])OFFSET=6;
35 else OFFSET=7;
}

```

The read address (ADDRESS_READ) generated in Equation 1 is separated into N_g

respective areas, the number of read addresses in each respective area is 2^m , and the number of random address components generated by the pseudo random generator (PN generator) corresponding to each respective area is 2^m-1 .

5 The read address generated in accordance with Equation 1 is mapped with the original address on a one-to-one basis, and such an interleaver has the property of the PN interleaver and the distance property. Here, $\text{OFFSET}(\text{ADDRESS_READ}, \text{GTH})$ is a function for determining to which group the read address belongs, and shifting the address by the offset value.

10 When a specific address of the interleaver memory is addressed to read data without shifting the address by the offset value, a number of invalid data bits are read equal to the number of the offset values. That is, 8 invalid read addresses corresponding to the offsets [L, ..., N-1] exist between interleaving sequences, in addition to the read addresses
15 corresponding to the input data bits [0, ..., L-1], as shown in FIG. 4. In this case, since N data bits (where $N=\text{OSV}+L$, $\text{OSV}=8$) are transmitted, it is necessary to delete the addresses existing between the interleaving sequences and connect the addresses. This will be described with reference to FIG. 5.

20 For example, when one of several combinations which can express the newly calculated virtual interleaver size N in terms of $N_g \times 2^m$ is selected, the size of each address generation area is determined. An invalid address generated by the offset value (OSV) is determined based on an initial value of a PN generator, generated in the last address generation area. A position GTH (Group Threshold) of the invalid address depends on how
25 the whole addresses are generated. In other words, when generating an address using a PN generator corresponding to its associated address generation area, the position is determined based on how to (i.e., sequentially or randomly) select the initial value of each PN generator and the address generated in each address generation area. That is, when the interleaving rule is known, it is possible to know the position where the invalid address is generated by the
30 added offset value.

35 This means that it is possible to sequentially output the interleaved stored data bits excluding the invalid data bits corresponding to the invalid addresses. More specifically, the read addresses corresponding to the last 8 stored data bits [L, ..., N-1] out of the stored data bits are determined regularly according to the interleaving rule. Therefore, it is possible to previously know the positions of the interleaved invalid data bits. Assume that the addresses for 8 tail data bits are D1, D2, D3, ..., D8 [i.e., L, ..., N-1], and an interleaving address corresponding to each address Di (i=1, ..., 8) is $T_k=\text{PRIB}(D_i)$, where $k=1, \dots, 8$. Of course, it

- 11 -

is not always true that $T_1 < T_2$ for $D_1 < D_2$, and the interleaving address is arranged in a given order. Therefore, for convenience, assume that an index controlled to arrange the interleaving address in order of $T_1 < T_2 < \dots < T_8$ is defined as 'j' and an address using this is defined as T_j ($j=1..8$). Then, N interleaving areas are divided into 8 groups on the basis of the addresses, and each T_j becomes a threshold for distinguishing a boundary thereof. Here, the addresses should be connected by excluding the thresholds. For example, all the generated addresses will have values between $[0, \dots, L-1]$, by generating a read address 0 for G_0 , a read address 1 for G_1 , ..., and a read address 7 for G_7 .

A hardware structure implemented for the algorithm of Equation 1 is shown in FIG. 7. In particular, FIG. 7 shows a detailed structure of the address generator 211 for reading the data stored sequentially in the interleaver memory 112 by interleaving according to an embodiment of the present invention.

Referring to FIG. 7, a random address generator 221 generates random address components using a plurality of PN generators. A comparator 222 compares the random addresses output from the random address generator 221 with the thresholds GTH (i.e., group values for grouping the address areas) previously determined by the offset value to determine to which group they belong, and outputs a group select signal and the random addresses. Further, the comparator 222 compares the random addresses output from the random address generator 221 with the group thresholds GTH determined by the offset value and deletes the corresponding random address when any one of them is identical. A selector 223 selects the corresponding group value in response to the select signal. A subtracter 224 subtracts a specific group value output from the selector 123 from the random address output from the comparator 222, and generates a read address for reading the data from the interleaver memory 212.

FIG. 8 shows the detailed structure of the random address generator 221 of FIG. 7. Referring to FIG. 8, PN generators 811-8N1 generate PN sequences, which are address components, for changing the sequence of the data bits stored in the associated address generation areas, and provide the generated PN sequences to a first multiplexer 812. The respective PN generators 811-8N1 are initialized to different initial values. A counter 816 generates a select signal for selecting an output of the first multiplexer 812. If the number of address areas is N_g , the counter 816 generates the select signals of $0..N_g-1$. The select signals can be generated either sequentially or randomly. In random generation, the select signals are generated randomly according to a predetermined pattern, determined through an algorithm, which will be described below. The multiplexer 812 selects the output of the PN generators according to the select signals provided from the counter 816. The output data of the

- 12 -

5 multiplexer 812 is subtracted by a value of 1 in a subtracter 818 and provided to a second multiplexer 813. This is because the PN generators cannot generate the address value 0. Therefore, all the generated values are subtracted by 1 so as to map the random addresses from the address value 0. An area (or group) counter 815 generates a count value
10 corresponding to the address generation area size and provides the generated count value to a comparator 814. The comparator 814 outputs a select signal '1' to the second multiplexer 813, when the count value provided from the area counter 815 corresponds to an area size 2^m-1 . The second multiplexer 813 selects the output of the first multiplexer 812 according to the select signal, when the count value output from the area counter 815 is lower than or equal to 2^m-2 , and selects 2^m-1 provided from the comparator 814, when the count value reaches 2^m-1 . An address buffer 817 stores the output data of the counter 816 in a high address area, and the output data of the second multiplexer 813 in a low address area. The addresses stored in the address buffer 817 are provided to the comparator 222 of FIG. 7. Referring again to FIG. 7, the comparator 222 then determines to which group the addresses belong, and provides the
15 group select signals to the selector 223. The selector 223 selects the corresponding group values according to the select signals. The subtracter 224 subtracts the offset value of selected group values from the addresses output from the comparator 222 to provide the final addresses to the interleaver memory 212, and reads the data corresponding to the read addresses from the interleaver memory 212.

20 A procedure for generating the read addresses will be described with reference to FIGS. 7 and 8. The PN generators 811-8N1 generate PN sequences by shifting the stored state values by clocking to generate PN sequences, and the first multiplexer 812 selects states of the PN generators 811-8N1 according to the select signals provided from the counter 816.
25 When the states of the PN generators are all selected according to the select signals, the PN generators 811-8N1 generate PN sequences by shifting the stored states by clocking. The PN sequences output from the first multiplexer 812 are subtracted by 1 and applied to the second multiplexer 813. The PN sequences are provided to the low address area of the address buffer 817 until the address count value counted in the area counter 815 is lower than the address generation area size value 2^m-1 .
30

35 However, when the address count value reaches the address generation area size 2^m-1 , the value 2^m-1 is provided to the low address area of the address buffer 817. The address buffer 817 stores in the high address area the values indicating the address generation areas corresponding to the presently selected PN generators, output from the counter 816. The addresses stored in the address buffer 817 are provided to the comparator 222, and the comparator 222 determines to which group the addresses belong and provides the select signals for the group values to the selector 223. The addresses are provided to the subtracter

- 13 -

224. The selector 223 then selects the corresponding group value according to the select signal, and the subtracter 224 subtracts the corresponding offset value of selected group value from the address value output from the comparator 222, to provide a read address to the interleaver memory 212. However, when the address does not belong to any group, i.e., when the address corresponds to the threshold values, the comparator 222 deletes the address, regarding the address as an invalid address. The interleaver memory 212 outputs the data stored in the corresponding address according to the provided read address.

With reference to FIG. 9, a description will be made of a procedure for generating an interleaving address in the address generator 221. The procedure of FIG. 9 is based on the algorithm of Equation 1.

Referring to FIG. 9, the address generator 221 (or a general CPU) calculates respective parameter values for interleaving in step 911. The address generator 221 determines the virtual address size N by adding a proper value (i.e., offset value) such that the number of zero bits from the LSB should be at least one, when the input frame size L is converted to a binary value. Further, when the virtual address size N is expressed in terms of a power of 2 ($2^m \times N_g$), the value m and the group number N_g are determined through an algorithm, which will be described later. The parameters are previously fixed in the designing process, and these values are stored in a look-up table. During interleaving, the corresponding values are read from the look-up table.

The address generator 221 initializes the write address to '0' in step 913, and initializes a group index 'g' to '0' in step 915. After initialization, the address generator 221 calculates the random address using the PN sequence in accordance with a formula below in step 917.

$$\text{ADDRESS_READ} = (\text{PN}_g(\text{ADDRESS_WRITE}) - 1) + g \cdot 2^m$$

where $\text{PN}_g(\text{ADDRESS_WRITE})$ denotes a function for generating the PN sequence and is subtracted by 1 to map the generated PN sequences from 0. Further, $+g \cdot 2^m$ is to map the generated PN sequence into the corresponding area. That is, when the group index is $g=0$, the generated PN sequence is mapped into the area 0, and when the group index is $g=1$, the generated PN sequence is mapped into the area 1.

The address generator 221 calculates the final read address using the calculated PN address in accordance with a formula below, in step 919.

$$\text{ADDRESS_READ} = \text{ADDRESS_READ} - \text{OFFSET}(\text{ADDRESS_READ}, \text{GTH})$$

The above formula defines an address calculated by determining to which group the read address belongs and subtracting the offset value of the selected group value corresponding to the determined group therefrom. The above group is distinguished by the group value, such as the interleaved addresses which are generated by the offset value (=invalid address). For example, when the read address corresponds to the group 1, the read address is subtracted by 1, and when the read address corresponds to the group 2, the read address is subtracted by 2.

Thereafter, the address generator 221 examines in step 921 whether the group index 'g' has reached the read number N_g-1 . When the group index has reached N_g-1 , the address generator 221 proceeds to step 923. Otherwise, when the group index has not reached N_g-1 , the address generator 221 proceeds to step 925 to increase the group index by 1 and returns to step 917. Meanwhile, upon detecting that the group index has reached the group number N_g-1 , the address generator 221 examines in step 923 whether the write address has reached a value 2^m-2 (the number of addresses which can be generated by one PN generator). Here, the write address corresponds to the area counter. When the write address has reached the value 2^m-2 , the address generator 221 proceeds to step 929. Otherwise, when the write address has not reached the value 2^m-2 , the address generator 221 proceeds to step 927 to increase the write address by 1 and returns to step 915.

In step 929, the address generator 221 maps the write address into the read address of each area using a formula below, and then ends the program.

$$\begin{aligned} \text{ADDRESS_WRITE} &= 2^m-1; \\ \text{ADDRESS_READ} &= \text{ADDRESS_WRITE} + g*2^m - \text{OFFSET}(\text{ADDRESS_WRITE}) \end{aligned}$$

That is, it means that the last write address is used for the read address. That is, since each address generator can generate only 2^m-1 addresses in maximum, the last write address is used for the read address.

Tables 1 and 2 below show OCPNI design parameters for each Rate Set when the interleaving method according to the present invention is applied to an IMT-2000 system.

[Table 1]

Rate Set 1	@19.2kbps	@38.4kbps	@76.8kbps	@153.6kbps	@307.2kbps
Interleaver	376	760	1528	3064	6136

- 15 -

Size L					
OSV	8	8	8	8	8
N=L+OSV	384	768	1536	3072	6144
M	6	7	8	9	10
N _g	6	6	6	6	6
Initial Parameter	101011	1010110	10101101	101011010	1010110101
	010100	0101001	01010010	010100101	0101001010
	111011	1110110	11101101	111011010	1110110101
	101111	1011111	10111110	101111101	1011111010
	011101	0111010	01110101	011101010	0111010101
	011010	0110101	01101010	011010101	0110101010
GTH{t0,t1,t2,t3,t4,t5,t6,t7}	{23,41,65,107,119,131,269,383}	{47,77,191,335,401,425,641,767}	{491,599,737,755,1187,1211,1265,1535}	{659,1373,2027,2447,2531,2825,2861,3071}	{881,2159,2429,2807,4307,4559,4931,6143}
PN Generator Polynomial p(x)	[1100001]	[10010001]	[101110001]	[1000100001]	[1001000001]

[Table 2]

Rate Set 2	@28.8kbps	@57.6kbps	@115.2kbps	@230.4kbps	@460.8kbps
interleaver Size L	568	1144	2296	4600	9208
OSV	8	8	8	8	8
N=L+OSV	576	1152	2304	4608	9216
m	6	7	8	9	10
N _g	9	9	9	9	9
Initial Parameter	101011	1010110	10101101	101011010	1010110101
	010100	0101001	01010010	010100101	0101001010
	101010	1010100	10101001	101010010	1010100101
	011011	0110111	01101110	011011101	0110111010
	001011	0010110	00101101	001011010	0010110101
	111100	1111001	11110010	111100101	1111001010
	110111	1101110	11011101	110111010	1101110101
	100011	1000111	10001110	100011101	1000111010
	110000	1100000	11000001	110000010	1100000101

- 16 -

GTH{t0,t1,t2,t3,t4,t5,t6,t7}	{107,305,332,368,431,449,467,575}	{179,224,395,611,710,746,1070,1151}	{485,647,854,881,1529,1565,1646,2303}	{197,323,764,818,2144,3185,4166,4607}	{2006,2384,2942,6074,7991,8396,8963,9215}
PN Generator Polynomial p(x)	[1100001]	[10010001]	[101110001]	[1000100001]	[1001000001]

In Tables 1 and 2, p(x) is a primitive polynomial of the PN generator determined on a Galois field GF(2), wherein the leftmost bit indicates a coefficient of 0th order of p(x) and the rightmost bit indicates a coefficient of the highest order. That is, p(x)=[1100001] indicates p(x)=1+x+x⁶. A PN generator corresponding to the generator polynomial p(x)=1+x+x⁶ is illustrated in FIG. 6.

In general, in the initialization process, the initial seeds corresponding to the respective areas are loaded on m shift register cells. Thereafter, the register values are updated every clock by the connected line, and after update, a 6-bit address is generated by the combination of the values (0/1) stored in the register. That is, when the content of the lowest order is p[1] and the content of the highest order is p[m], PN_g(ADDRESS_WRITE) indicates an address obtained by converting the shift register's binary value of (p[1]p[2]...p[m-1]p[m]) to a decimal number ($=p[1]2^{m-1} + \dots + p[m]2^0$) when clocking is performed at an initial time by write address ADDRESS_WRITE. In addition, the address generated from the PN generator has a period of 2^m-1. Further, since the initial seeds are not zero, all the generated addresses have the values within a range of {1≤k≤2^m-1}. Therefore, [PN_g(ADDRESS_WRITE)-1] has the value within the range of {0≤k≤2^m-2}. In this case, since the number, 2^m-1, of the addresses generated by the PN generator is smaller by one than the number, 2^m, of the required addresses, the last address in every area is overwritten and then used as the read address ADDRESS_READ. In Equation (1), this relation is expressed as follows:

$$\text{ADDRESS_WRITE} = \text{ADDRESS_WRITE} + g \cdot 2^m - \text{OFFSET}(\text{ADDRESS_WRITE})$$

Table 3 below shows OCPNI read addresses for an interleaver having a size of L=376 and generated based on Table 1.

[Table 3]

36 73 172 230 317 332 33 68 165 226 286 373 16 113 146 224 318 346 55 88
--

184	223	302	27	123	171	207	294	365	13	149	199	290	342	6	78	138	195	288	
50	118	180	193	287	364	40	106	169	192	271	357	35	100	148	239	262	338	17	97
185	215	259	8	80	156	203	257	363	51	119	189	197	256	341	25	91	158	194	303
330	12	77	190	240	279	372	53	70	174	231	267	361	26	114	166	211	261	340	60
104	162	201	258	45	99	160	196	304	348	22	81	159	241	295	58	72	143	216	275
350	44	115	135	251	265	37	89	131	221	260	366	18	76	129	206	305	358	56	117
128	246	280	354	43	90	175	234	315	352	21	124	151	228	285	351	10	109	139	225
270	335	52	86	133	208	310	327	41	122	130	247	298	323	20	108	176	219	292	321
57	101	167	205	289	320	28	82	147	198	272	367	61	120	137	243	311	343	30	107
132	232	283	331	62	85	177	227	269	325	46	74	152	209	262	322	38	116	187	200
306	368	34	105	157	243	296	359	32	84	142	217	291	339	31	121	182	204	272	329
15	92	170	245	264	324	7	125	164	218	307	369	3	94	161	252	281	344	1	126
144	237	268	1	110	183	214	309	349	47	102	155	250	282	334	23	98	141	236	316
374	11	96	134	229	301	362	5	95	178	210	278	356	2	79	168	248	314	353	48
71	163	235	300	336	39	67	145	213	293	375	19	65	136	202	274	347	9	64	179
244	312	333	4	111	153	233	299	326	49	87	140	212	277	370	24	75	181	249	266
360	59	69	154	220	308	355	29	66	188	253	297	337	14	112	173	222	276	328	54
103	150	254	313	371	42	83	186	238	284	345	63	127	191	255	319				

As described above, in the OCPNI according to the first embodiment of the present invention, the primitive polynomials of the PN generators or the initial seeds are determined through an algorithm described below, in the first embodiment, the invalid addresses GTH generated by the offset values are deleted by the comparator 222. However, in an alternative embodiment, since the PN generator 8N1 corresponding to the last area generates an invalid address (low address GTH) caused by the offset value, there is a method of essentially preventing generation of such invalid address. In this case, the deletion function of the comparator 222 is unnecessary.

Next, a detailed description will be made of an interleaving device for essentially preventing generation of the invalid addresses according to a second embodiment of the present invention.

A main idea of the OCPNI is to determine a new frame size N by adding an offset value OSV to the interleaver size L , and then divide the virtual interleaver size N into N_g areas to permute each group element using the PN generator. The PN generators generate 2^m address components. Since the last PN generator ($g=N_g-1$) generates the invalid address caused by the OSV, it is necessary to delete this invalid address so that the total address number generated by the OCPNI address generation block should be L . Therefore, the

invention implements a control logic which monitors the address generated from the last PN generator ($g=N_g-1$ designated in the step 923 in Fig. 9) to skip selection of the PN generator when the address is the invalid address caused by the added offset value.

First, if it is assumed that the interleaver size $L=60$, offset value $OSV=4$, virtual interleaver size $N=64$, generator polynomial's order $m=4$ and group number $N_g=4$, then the number of the PN generators is 4 and each of them has a period of 15. Further, assume that the PN sequence generated by the last PN generator is given as shown in Table 4 below.

[Table 4]

Time k:	0	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15
PN3(k):	5	1	13	2	7	15	14	3	6	4	8	12	9	11	10	
PN3(k)-1:	4	0	12	1	6	14	13	2	5	3	7	11	8	10	9	

As shown in Table 4, a state value $PN3(k)$ generated from the last PN generator ($g=N_g-1$) becomes a read address for interleaving the frame data corresponding to the last group, stored in the interleaver memory. Therefore, for $OSV=4$ and $m=4$, the 12th, 13th, 14th and 15th addresses of the last group are the invalid addresses. Thus, in this case, the invalid addresses generated from the last PN generator are skipped to the first PN generator. Here, when the PN generators are sequentially selected from the 0th PN generator, the value determined by subtracting '1' from the address generated by the last PN generator is used as a low address for the read address. Therefore, when the last PN generator generates one of the 13th, 14th and 15th addresses, the 0th PN generator is selected rather than the last PN generator. Further, the invalid address according to $15(PN3(k)-1)$, which the last PN generator cannot generate, is prevented from being generated by blocking the clock signal or ignoring it by not using even though it is generated. Meanwhile, when the PN generators are randomly selected, the last PN generator may not be selected at the last address of one frame. In this case, the last address (2^m-1) is not used, skipping to the next PN generator.

In consideration of the foregoing description, an OCPNI interleaving addresses generating algorithm according to the second embodiment of the present invention can be expressed as shown in Equation 2 below.

[Equation 2]

/* OCPNI-2 Program*/

- 19 -

/* N: frame length (=L+OSV) GL: group length 2^m N_g : group number*/

For (clk=0; clk<N- N_g ;clk++)

{ g=clk % N_g ;

5 READ_ADDRESS=PNg()-1 + g*GL;

active=(READ_ADDRESS<L)? ON:OFF;

if (active==ON) {printf ("%d\n",READ_ADDRESS);}

}

for (g=1; g< N_g ; g++)

10 { READ_ADDRESS=GL*g-1;

printf ("%d\n",READ_ADDRESS);

}

The algorithm of Equation 2 can be implemented using the hardware of FIG. 10. Referring to FIG. 10, PN generators 11-14 generate PN sequences for changing the sequence of the data bits stored in the associated address generation areas and provide the generated PN sequences to a first multiplexer 16. The respective PN generators are initialized to an optimal state value determined through an algorithm, which is described below. This will be described later in detail with reference to a method for determining initial seeds of the PN generators. A counter 19 generates a select signal for selecting an output of the first multiplexer 16. If the number of the address areas is N_g , the counter 19 generates the select signals of 0.. N_g -1. The select signals can be generated either sequentially or randomly. In random generation, the select signals are generated randomly according to a predetermined pattern, determined through an algorithm. The multiplexer 16 selects the output of the PN generators according to the select signals provided from the counter 19. The output data of the multiplexer 16 is subtracted by 1 in a subtracter 23 and provided to a second multiplexer 15. This is because the PN generators cannot generate the address value 0. Therefore, all the generated values are subtracted by 1 so as to map the random addresses from the address value 0. An area (or group) counter 24 generates a count value corresponding to the address generation area size and provides the generated count value to a comparator 17. The

- 20 -

comparator 17 outputs a select signal '1' to the second multiplexer 15, when the count value provided from the area counter 24 corresponds to an area size 2^m-1 . The second multiplexer 15 selects the output of the first multiplexer 16 according to the select signal, when the count value output from the area counter 24 is lower than or equal to an area size 2^m-2 , and selects the area size value 2^m-1 provided from the comparator 17, when the count value reaches the area size value 2^m-1 . An address buffer 22 stores the output data of the counter 19 in a high address area, and the output data of the second multiplexer 15 in a low address area. The addresses stored in the address buffer 22 are used as addresses for reading the data from the interleaver memory.

An OSV detector 18 receives a state of the last PN generator 14 and the count signal of the counter 19, and provides a reset signal Load_Zero to the counter 19 when it is determined that the PN generator to be selected next according to the count signal is the last PN generator 14 and the state value of the PN generator 14 is an invalid state value (hereinafter, referred to as an offset state value) caused by the added offset value. The counter 19 then generates a select signal for skipping the last PN generator 14 and selecting the next PN generator. If counter 19 is designed to sequentially select the PN generators, the counter 19 will generate a select signal for selecting the first PN generator. Alternatively, if counter 19 is designed to randomly select the PN generators, the counter 19 will generate a select signal for selecting a next PN generator according to a predetermined pattern. At this point, the OSV detector 18 determines whether the present state value stored by AND-OR-ing connection of the last PN generator is the offset state value caused by the added offset value, to output the reset signal Load_Zero. Here, AND-OR-ing connection of the last PN generator is determined according to the shift register cell number m and the offset value OSV.

When OSV is a constant, AND-OR-ing connection of the PN generator has a constant rule so that it is very simple to implement. For example, for $m=4$ and $OSV=4$, the AND-OR-ing connection is implemented as shown in FIG. 12. Referring to FIG. 12, the lower two register cells undergo OR-ing and the higher two register cells undergo AND-ing. This is, the AND-OR-ing connection is provided to skip $(OSV-1)$ PN addresses corresponding to the 13th, 14th and 15th PN sequences in the last PN generator, because for $m=4$, the PN generator generates the PN sequences of 1 to 15, and the offset value is $OSV=4$. Further, the reset signal Load_Zero is generated by AND-ing the output of the AND gate, the output of the OR gate and an inverted output signal of the counter 19. When the PN generators are selected randomly, the last PN generator may not be selected at the last addresses of one frame, the forcedly made last value 2^m-1 is skipped.

A first logic operator 20 receives the symbol clock SYM_CLK and the count value

output from the counter 19, and generates a clock for updating the state values of all the PN generators 11-14 when the count value is logic '0' and the symbol clock is at the rising edge. A second logic operator 21 receives the symbol clock and the count value output from the counter 19, and provides the area counter 24 with a clock for the next counting, when the count value is logic '0' and the symbol clock is at the falling edge.

A procedure for generating the read addresses will be described with reference to FIG. 10. The PN generators 11-14 generate PN sequences by shifting the stored register cell values at every clock provided from the first logic operator 20 to generate PN sequences, and the first multiplexer 16 selects a state of the PN generator according to the select signal provided from the counter 19. The PN sequences output from the first multiplexer 16 are subtracted by 1 in the subtracter 23 and applied to the second multiplexer 15. The PN sequences are provided to the low address area of the address buffer 22 until the address area count signal of the area counter 24 is lower than the address generation area size 2^m-1 . However, when the address count signal reaches the address generation area size 2^m-1 , the value 2^m-1 is provided to the low address area of the address buffer 22. The address buffer 22 stores in the high address area the count value output from the counter 19. The values stored in the address buffer 22 are used as addresses for reading the data stored in the memory. The OSV detector 18 receives the state of the last PN generator 14 and the count value of the counter 19, detects the offset state value from the last PN generator 14, and provides the counter 19 with the reset signal Load_Zero, when the count value indicates the previous PN generator 13 of the last PN generator 14 according to the predetermined order. The counter 19 then skips selection of the last PN generator 14 so that the first multiplexer 16 should not output the detected offset state, and provides the first multiplexer 16 with a select signal for selecting the PN generator 11. Meanwhile, the count value (which is identical to the select signal) of the counter 19 is provided to the first and second logic operators 20 and 21. The first logic operator 20 receives the count value and the symbol clock, and provides the PN generators with the clock when the count value is '0' and the symbol clock is at the rising edge. The PN generators then update the states according to the symbol clock. The second logic operator 21 receives the count value and the symbol clock, and provides the area counter 24 with the clock when the count signal is '0' and the symbol clock is at the falling edge. The area counter 24 provides the count value to the comparator 17 in response to the clock. Here, the area counter 24 counts a select period of the PN generators. Further, the comparator 17 compares the count value provided from the area counter 24 with the predetermined value 2^m-1 , and outputs the select signal to the second multiplexer 15 when the count value is 2^m-1 so as to provide the value 2^m-1 to the low address area of the address buffer 22. That is, the second multiplexer 15 provides the subtracted-by-one PN sequence to the low address area of the address buffer 22 when the number of the select periods of the PN

generators is lower than 2^m . However, when the number of the select periods of the PN generators is 2^m , the second multiplexer 15 provides the value 2^m-1 to the low address area.

As stated above, the second embodiment implements a simple logic capable of skipping selection of the offset state of the last PN generator 14 so as to prevent generation of the invalid addresses caused by the added offset. Therefore, the second embodiment does not require the logic circuits (comparator 222 and selector 223 and the operator 224) for deleting the generated invalid addresses in the first embodiment.

FIG. 11 shows a timing diagram for explaining the procedure for generating the read addresses. Herein, it is assumed that the interleaver size $L=60$, offset value $OSV=4$, virtual interleaver size $N=64$, generator polynomial's order $m=4$ and group number $N_g=4$.

Referring to FIG. 11, SYM_CLK indicates the symbol clock, and SEL_MUX indicates a select signal for selecting the PN generator. Further, PN[0] indicates a register value of the first PN generator, PN[1] indicates a register value of the second PN generator, PN[2] indicates a register value of the third PN generator, and PN[3] indicates a register value of the last PN generator. Load_Zero indicates a signal for resetting the select signal SEL_MUX so as to skip selection of the last PN generator PN[3] when SEL_MUX is 2 and PN[3] is an invalid value caused by the offset. Further, UP-Counter indicates the area counter, and Address_Read indicates a read address. In addition, a first clock indicates a clock for updating state values of the PN generators, and a second clock indicates a clock, provided from the area counter 24, for counting the number of select periods of the PN generators.

As illustrated, when the Load_Zero signal is enabled, SEL_MUX is reset, responsive to which the first and second clock signals are enabled. Therefore, although the PN generators are not all selected, states of the PN generators are updated according to the first clock and UP_Counter is enabled according to the second clock. That is, the read address is made by skipping the last PN generator and using the register value of the first PN generator. As a result, the finally generated read addresses are $0+a$, $16+b$, $32+c$, $48+d$, $0+e$, $16+f$, $32+g$, (h skipped), $0+i$, $16+j$, $32+k$,... And, in case that the final state of the up-counter is 2^m-1 , which is 15 in this example, the read address is $0+15$, $16+15$ and $32+15$ regardless of the state of PN(0)~PN(3).

With reference to FIG. 13, a detailed description will be made of a procedure for generating the read address according to the second embodiment of the present invention.

In step 1301, a virtual address area N is determined by adding an offset value OSV to the input frame size L . Then, in step 1303, the virtual address area is divided into a plurality (N_g) of address generator areas. Thereafter, in step 1305, random addresses are generated according to the respective address generation areas using the PN generators. In step 1307, the random addresses generated in the respective address generation areas are randomly selected. Alternatively, it is also possible to sequentially select the random addresses generated in the respective address generation areas. In this process, the OSV detector 18 examines whether the random sequence generated by the PN generator corresponding to the last area is an invalid value caused by the added offset value. If it is determined that the generated random sequence is an invalid value, the procedure goes to step 1311 where the random address generated in the last area is not selected (or skipped). Otherwise, when the generated random sequence is not an invalid value, the procedure goes to step 1313 to examine whether the present area count value corresponds to 2^m-1 (where m denotes the state number of the PN generator). When the area count value does not correspond to 2^m-1 , a read address is generated in accordance with a formula $READ_ADDRESS = PN_g() - 1 + (g * GL)$ in step 1315. However, when the area count value corresponds to 2^m-1 , the procedure proceeds to step 1317 where the read address is generated in accordance with a formula $READ_ADDRESS = GL * g + (2^m - 1)$.

As described above, the OCPNI according to the second embodiment of the present invention contributes to a reduction in the complexity. Therefore, the parameters according to the rates of the CDMA-2000 forward Supplemental Channel require only the PN generator polynomial, initial register value and OSV. When it is implemented by Equation 1, the group threshold values GTH are not required.

Next, reference will be made to the parameters which should be basically determined in designing the OCPNI according to the second embodiment of the present invention. The basic parameters include the number, N_g , of groups and the order, m , of PN generator polynomial according to a given interleaver depth. In the early design process, it is difficult to determine the optimal N_g and m for the frame size of the CDMA-2000 system. Therefore, the values were determined through an algorithm, which will be described below. The determined parameters are shown in Tables 1 and 2. For example, in Rate Set 1 of the CDMA-2000 system, $N_g=6$ for all the frame sizes, based on which the value 'm' is determined. This is to prevent a decrease in the random property in each group, when N_g is excessively high. That is, when $N_g=6$ for $N=384=6 \times 2^6$, $m=6$. Therefore, the data is randomly read at $2^6=64$ addresses per group. Further, the OCPNI which is a 2-dimension interleaver can satisfy the distance property to a some extent.

- 24 -

However, in the first embodiment, a decrease in the frame size FL causes an increase in E_b/N_0 , thus blunting improvement of BER/FER, so that its slope is lower than that of a BER/FER curve of a $K=9$ convolutional encoder. That is, when E_b/N_0 constantly increases, it is expected that the turbo encoder will perform worst than the conventional encoder. This phenomenon is related to a weight spectrum of the turbo encoder. Therefore, in the second embodiment, all three parameters are considered for optimization of the OCPNI.

As described above, the OCPNI has the parameters N_g and m . Further, the generator polynomials are used for operating the PN generators in the respective groups, and selection of them is another parameter. Finally, with regard to the parameter related to the initial state value of each PN generator, too many combinations exist. Therefore, it is difficult to detect an optimal initial state value using the full search.

As a result, for improvement of the least weight and the overall weight spectrum, (1) N_g is determined, (2) a generator polynomial is selected, and (3) when the least weight is not satisfactory, an initial state value of the PN generator belonging to a group corresponding to the least weight is controlled. In general, it is possible to obtain a turbo interleaver having better performance by repeatedly performing this method several times. This is because a computer search is not effective due to too many combinations of the parameters. First, the functions and parameters will be defined and then an optimal interleaver will be searched using the algorithm of Equation 3 below.

W : Weight Distribution Vector

D(.): Decision Criteria Function

D(W)=1 if W is satisfactory

D(W)=0 if W is not

[Equation 3]

1. Initialize PN generator PN_i with initial seed vector $Seed_i \in \{0,1\}$
- for $i=0, \dots, N_g-1$
 - Choose arbitrary primitive polynomial $G(x)$ of order M
 - Choose information sequence I 's that are expected to generate the minimum weight code
 2. For a given Turbo Encoder E , computer W
 3. If $D(W)=1$, go to 6
 4. Find PN generator PN_k associated with minimum weight of W
 5. Change $Seed_k$ such that $weight(Seed_k, Seed_i)=1$ and go to 2
 6. stop

- 25 -

In the algorithm of Equation 3, to reduce the search time, the best $G(x)$ is first selected in a given state and then the algorithm is used. Generally, it is possible to find an interleaver satisfying a given condition after repeating the search three or four times. Of course, although the best $G(x)$ also depends on the initial state (or seed), it is preferable to first select $G(x)$ since the number of the generator polynomials is much lower than the types of the states. Therefore, selection of $G(x)$ is regarded as a coarse estimation process of the interleaver. Such a designed OCPNI has a better weight property than the method performed through experiments and intuition. In general, this guarantees a better BER/FER performance.

Now, a description will be made of a method for optimizing the initial register value.

For example, assume that the initial state value is optimized for 4 PN generators. Since $m=5$ and $N_g=4$, the state values are initialized as follows:

Group 0 : 0 1 0 1 0

Group 1 : 1 0 1 0 1

Group 2 : 0 0 1 1 0

Group 3 : 1 1 0 0 1

Assume that the weight distribution of FIG. 5 is generated by calculating the generated weight of the OCPNI turbo interleaver.

[Table 5]

Weight	22	32	33	62	62	62	63
Address	44	92	8	76	111	124	56
Group	1	2	0	2	3	3	1

In this case, the presently required minimum distance is about 60, the initial state value of the PN generator corresponding to a group having the weight 22, 32 and 33 should be changed. That is, the initial state value of the PN generator corresponding to the groups 1, 2 and 0 should be changed. In general, since the corresponding PN generator does not affect the weight corresponding to another group, it is possible to delete the cases where the weight is lower than 60, by changing the corresponding initial state value.

In this case, assume that the initial state value of the group 1 is controlled as follows to obtain the weight distribution of Table 6.

Group 0 : 0 1 0 1 0

- 26 -

Group 1 : 1 0 1 1 1

Group 2 : 0 0 1 1 0

Group 3 : 1 1 0 0 1

[Table 6]

Weight	32	33	62	62	62	63
Address	92	8	76	111	124	56
Group	2	0	2	3	3	1

In this case, since the minimum distance is 32, an initial state value of the group 2 corresponding to the minimum distance 32 is controlled. It is possible to obtain the OCPNI turbo interleaver having the minimum distance of 62 by repeating this process. The obtained weight distribution is shown in Table 7 below.

[Table 7]

Weight	62	62	62	63
Address	76	111	124	56
Group	2	3	3	1

FIG. 14 shows a procedure for optimizing the initial state value of the PN generators.

Referring to FIG. 14, in step 1401, the PN generator of each area is initialized using an arbitrary state value, the generator polynomial of each PN generator is determined, and then a predetermined input word for determining the minimum weight is selected. Thereafter, the OCPNI interleaver is enabled in step 1403 and a Hamming weight of the turbo encoder output from the turbo encoder is determined in step 1405. In step 1407, the weight distribution is calculated and then the minimum weight is determined. It is determined in step 1409 whether the determined minimum weight satisfies a threshold value. When the minimum weight satisfies the threshold, the procedure goes to step 1411 to determine whether the search has been performed for all the predetermined input words. When the search is completed for all the predetermined input words, the procedure is ended. Otherwise, when the search is not completed for all the predetermined input words, the procedure returns to step 1401 to select a predetermined input word for another case for determining the minimum weight and then repeats the succeeding steps. Meanwhile, when the minimum weight does not satisfy the threshold in step 1409, an area having the minimum weight is searched in step 1413 and the initial state value of the PN generator corresponding to this area is changed. Thereafter, the procedure returns to step 1403 to repeat the succeeding steps. Here, the "predetermined input word" refers to a shifted information stream comprised of 2^m -

- 27 -

1 bits for an m-bit PN generator.

Tables 8 and 9 below show the parameters of the OCPNI according to the second embodiment of the present invention.

[Table 8]

Rate Set 1	@19.2kbps	@38.4kbps	@76.8kbps	@153.6kbps	@307.2kbps
interleaver Size L	376	760	1528	3064	6136
OSV	8	8	8	8	8
N=L+OSV	384	768	1536	3072	6144
M	6	7	8	9	10
N _g	12	12	12	12	12
Initial Parameter	11101	111000	1100101	01010111	100100110
	00101	001010	1111010	01101001	101011010
	11001	110000	1110101	01110111	11100110
	11100	111010	1100001	01011111	110110110
	00111	100111	1011011	00101011	101011110
	10001	001101	1010100	00110100	111100000
	10101	000101	1000100	00010101	100100010
	11000	110010	1110001	01111111	111110110
	00100	001000	1011110	01100001	111001010
	00001	000010	1001010	00001001	110011010
	11010	001011	1011000	00101101	111010110
	01100	110101	1111111	01100011	100001110
PN Generator Polynomial p(x)	[110111]	[1011011]	[10011101]	[101100011]	[100001000 1]
[AND]- [OR]-ring condition For N _g -1'th PN Generator	[11]-[111]	[111]-[111]	[1111]-[111]	[111111]- [111]	[111111]- [111]

In Table 8, [111]-[111] of [AND]-[OR]-ing means that PN[5:3] which is a PN generator cell of the corresponding position undergoes AND-ing and PN[2:0] undergoes OR-ing.

[Table 9]

Rate Set 2	@28.8kbps	@57.6kbps	@115.2kbps	@230.4kbps	@460.8kbps
Interleaver Size L	568	1144	2296	4600	9208
OSV	8	8	8	8	8
N=L+OSV	576	1152	2304	4608	9216
m	6	7	8	9	10
N_g	18	18	18	18	18
Initial Parameter	01100	100110	0101011	11110101	001101101
	01001	011010	1110001	00111001	101100100
	11111	000101	0001010	01010100	000001001
	11111	101110	1010110	01000111	101011000
	11111	111010	0101011	11010101	010001101
	11100	001110	1101101	00111001	101100100
	11100	100000	0001111	11001101	000011101
	10000	010001	1010110	01000111	100111000
	01110	011100	0101000	10010011	011000001
	11111	000101	0111011	11010011	001001101
	11100	010011	0001111	00000111	100001110
	11001	010001	0001010	10100111	001011001
	10010	000111	1111000	00101111	1100001000
	11111	011101	1111110	10101001	001101101
	01110	011101	1110001	00111001	110000110
	11001	010001	0001111	00101110	000011101
	11111	010001	1010110	01100101	110001000
	01100	001110	0000100	11010011	100111111
PN Generator Polynomial p(x)	[111011]	[1100111]	[11001011]	[111100111]	[110110110]
[AND]-[OR]-ring condition For N_g -1'th PN Generator	[11]-[111]	[111]-[111]	[1111]-[111]	[11111]-[111]	[111111]-[111]

For example, when the interleaver size is L=376 in Table 8, the determined read

addresses of the OCPNI are shown in Table 10 below.

[Table 10]

28 36 88 123 134 176 212 247 259 288 345 363 24 52 90 109 147 190 220 235 257
310 332 357 26 60 89 102 137 183 216 229 256 315 336 354 25 56 76 115 132 171 218
226 278 301 350 373 12 58 80 105 148 165 217 245 283 294 343 362 16 57 94 100 156
162 204 234 269 307 331 369 30 33 87 116 152 181 208 241 262 297 325 360 23 48 75
124 154 170 222 232 275 292 322 370 11 62 69 120 153 177 215 242 265 308 341 5 55
66 122 140 168 203 253 260 316 330 366 2 43 85 121 144 178 197 238 276 312 337
367 21 37 74 108 158 189 194 239 284 314 328 359 10 34 81 112 151 174 213 231 280
313 338 355 17 53 72 126 139 175 202 227 282 300 349 353 8 42 82 119 133 167 209
225 281 304 334 352 18 49 93 107 130 163 200 224 268 318 335 374 29 40 78 101 149
161 210 246 272 311 327 14 50 79 98 138 160 221 251 286 299 323 365 15 61 71 117
145 182 206 237 279 293 321 358 7 46 67 106 136 187 207 230 267 290 320 371 3 47
65 113 146 173 199 243 261 309 342 361 1 39 64 104 157 166 195 233 258 298 347
356 0 35 86 114 142 179 193 228 277 305 333 372 22 91 125 143 169 192 244 266 296
326 27 32 77 110 135 164 214 252 273 306 339 13 54 70 111 131 180 219 248 264 317
329 6 59 83 103 129 188 205 250 274 302 324 19 45 73 99 128 184 198 249 285 303
340 364 9 38 68 97 150 186 211 236 270 295 348 368 4 51 84 96 155 185 201 240 271
291 344 20 41 92 118 141 172 195 289 346 375 31 63 95 127 159 191 223 255 287 319
351

5 Tables 11A and 11B below show weight distribution of the OCPNI according to the first and second embodiments of the present invention, respectively.

[Table 11A]

		Rate Set 1
L		Weight Distribution
376	(1)	14 22 30 30 30 34 34 34 34 34 34 36 38 38 41 45 46 46 48 49...
	(2)	26 30 30 30 30 34 35 38 41 42 42 42 43 44 44 47 50 50 50 50...
760	(1)	23 26 26 29 30 30 30 30 34 34 34 34 34 34 34 34 34 38 45...
	(2)	50 52 52 58 59 61 63 69 70 71 78 78 78 78 78 78 78 78 78...
1528	(1)	34 34 34 34 34 34 34 34 34 34 40 46 50 54 54 58 58 58 58...
	(2)	57 57 58 58 58 58 58 58 58 58 58 58 58 60 64 74 74 77 78 78...

- 30 -

3064	(1)	26 30 34 34 34 34 34 34 34 34 34 34 34 34 34 34 34 34 34 34 54...
	(2)	58 58 58 58 58 58 58 58 58 58 58 58 58 58 58 58 58 58 69 78 98 98...
6136	(1)	34 51 58 58...
	(2)	106 106...

[Table 11B]

Rate Set 2		
L		Weight Distribution
568	(1)	26 26 30 30 30 30 34 41 43 46 46 46 46 46 46 46 46 46 46 46...
	(2)	77 82 82 82 87 88 90 94 97 100 100 101 102 102 102...
1144	(1)	21 30 30 30 30 46 46 46 46 46 46 46 46 46 46 46 50...
	(2)	97 10 102 102 102 102 102 102 102 102 102 102 102 102 102...
2296	(1)	30 34 45 46 46 46 46 46 46 46 46 46 46 46 46 46 46...
	(2)	107 112 116 119 121 122 127 131 132 135 139 140...
4600	(1)	46 46 46 46 46 46 46 46 46 46 46 46 46 46 46 46 46...
	(2)	154 154 154 154 154 154 154 154 154 154 154 154 154 174...
9208	(1)	46 46 46 46 46 46 46 46 46 46 46 46 46 46 46 46 46...
	(2)	174 220 226 226 226 226 226 226 226 226 226 226 226 226...

It can be appreciated from Table 8 that the OCPNI according to the second embodiment has twice the performance in weight distribution than the OCPNI according to the first embodiment.

In conclusion, performance of the OCPNI is greatly affected by the group number N_g and is also related to the primitive polynomial. The excessive high N_g causes a decrease in each group size, which deteriorates the random property. Therefore, it is necessary to determine a proper N_g . For example, when $N_g=FL$, there is provided performance of an OCI (Offset Controlled Interleaver) which has inferior performance as compared to the OCPNI. The final object to be considered is to search for an optimal initial state value from the N_g and primitive polynomial.

The foregoing description has been made with reference to the CDMA-2000 system. For example, when the OCPNI according to the present invention is applied to a turbo

- 31 -

interleaver for the UNTS system, the following parameters can be obtained. Tables 12 and 13 below show the parameters for obtaining the best performance.

[Table 12]

interleaver Size L	320	640	1280	2560	3840	5120
OSV	0	0	0	0	0	0
N=L+OS V	320	640	1280	2560	3840	5120
M	5	6	7	7	8	8
N _g	10	10	10	20	15	20
See for PN generator	01100	010100	1000100	1010001	00100110	00100110
	11001	001010	1110111	0011000	01101000	01101000
	01100	010100	1111101	1010001	10100111	10100111
	10000	001010	0000111	0100010	01001001	10011010
	01100	011001	1111101	1001011	11100100	10100100
	00110	100101	1000100	1001011	01100000	01000000
	01010	000001	1001101	1001011	11000110	11000110
	00011	110011	1010001	0101110	00111010	00111010
	01100	110100	1000100	0011100	10110010	10010010
	00001	110011	1101001	0001110	00101010	10111001
				0001110	10111001	01000010
				1100010	00010101	01110101
				0001100	01101000	00011100
				1010011	01000000	01000000
				0100010	10001000	11011000
				0101111		11010111
				0101110		00011010
				0101100		10010111
				0101111		00101111
				0011110		01110100
PN generator p(x)	111011	1011011	11001011	11001011	1110011	111100111

[Table 13]

interleav	320	320	640	640	1280	2560	5120
-----------	-----	-----	-----	-----	------	------	------

- 32 -

er Size L							
OSV	0	0	0	0	0	0	0
N=L+O SV	320	320	640	640	1280	1280	5120
m	6	4	7	5	6	8	9
N _g	5	20	5	20	20	10	10
Seed for PN generato r	111101	1011	0001010	01011	010110	1110111 0	1100011 01
	110100	1011	0011110	00101	111001	0110100 0	1111001 10
	011001	1111	1000110 1	10100	001100	1000010 0	1010110 01
	110011	1001	1000011	01111	111111	1001011 0	0110100 11
	110100	1011	1010110	01111	011100	0100111 0	1011010 10
		1011		01111	101001	1100110 1	0011011 01
		1011		01111	111010	0101100 1	0001000 10
		1011		01010	011010	1010110 0	1010001 00
		0001		00101	111010	1001010 1	1011100 11
		1001		00001	000101	0000110 1	1101011 00
		0110		11110	101011		
		0111		10011	111000		
		0100		01101	010010		
		0111		00111	010000		
		1011		10100	011111		
		0010		01010	100100		
		1011		00101	010100		
		0010		11110	000100		
		1010		01101	011111		
		0001		10001	11000		
PN generato	1011011	11001	1100101 1	110111	1011011	1111001 11	1101101 101

r p(x)							
--------	--	--	--	--	--	--	--

Table 14 below shows the weight distribution occurring when the above parameters are used.

5

[Table 14]

interleaver Size	Minimum Weight/ N_g (-> number of group)
320	48/5,50/10,36/20
640	50/5,78/10,78/10
1280	90/10,74/20
2560	90/10,102/20
3840	130/15
5120	130/10,170/20

10

As described above, the turbo interleaver for the UMTS system does not add the offset value since all the frame sizes can be divided by 2^m . However, the UMTS specification has not yet given any definition to the frame size to be actually used. In other words, the above frame sizes are set for verification. Therefore, when the frame size is actually determined, the offset value OSV should be added according to the principle of the invention.

15

20

25

As described above, the novel method minimizes the memory capacity required for random interleaving while satisfying the random property, distance property and weight property during interleaving of the input data. Further, the proposed offset controlled interleaving method can solve the problem of the existing PN interleaving method wherein the interleaver size cannot be expressed in terms of the power of 2 and the large interleaver size decreases the memory utilization efficiency. In addition, when the interleaver size of each logical channel is not expressed in terms of the power of 2 in designing an interleaver for the IMT-2000 system, the interleaver size is very large. The present invention provides a method for solving this problem. Further, in the existing interleaving method, since the interleaving rule according to the respective interleaver sizes should be stored in a controller (CPU or host) of the transceiver, a separate storage area is required in the CPU memory in addition to the interleaver buffer. The present invention has solved this problem. That is, the hardware complexity is reduced by implementing an interleaver which can perform enumeration. In addition, the interleaver/deinterleaver transmission method for transmission/reception is very simple and uses the minimum memory capacity. That is, an interleaver memory capacity corresponding to the frame(interleaver) size L is required. Finally, the novel interleaver satisfies all the properties of the turbo interleaver and is similar

- 34 -

or superior in performance to the random interleaver. Therefore, the novel interleaver guarantees an average performance or better.

5 While the invention has been shown and described with reference to a certain preferred embodiment thereof, it will be understood by those skilled in the art that various changes in form and details may be made therein without departing from the spirit and scope of the invention as defined by the appended claims.

CLAIMS:

1. A device for generating L addresses, which are smaller in number than $2^m \times N_g$ virtual addresses, for reading data from an interleaver memory in which L data bits are stored, the device comprising:

a selection circuit including N_g PN (Pseudo Noise) generators each including m memories, wherein one of the PN generators generates (OSV-1) offset values (OSV) satisfying $OSV = 2^m \times N_g - L$ and $(2^m - OSV)$ non-zero states in response to a first clock signal, and the other PN generators each generate $(2^m - 1)$ non-zero states, wherein the selection circuit periodically selects the PN generators according to a predetermined order in response to a select signal and outputs a state generated from the selected PN generator;

means for detecting each offset state from one PN generator, providing said select signal for not selecting said one PN generator so that the detected offset state is not output, and generating high address bits related to each selection of the PN generators in response to clock pulses of a second clock signal having a shorter period than the first clock signal;

means for generating low address bits determined by subtracting one from each state output from the selection circuit when a number of selection periods of the PN generators is smaller than 2^m , and generating low address bits corresponding to $2^m - 1$ when the number of selection periods is 2^m ; and

an address buffer for storing the addresses, said L addresses each being comprised of the high address bits and the low address bits.

2. The device as claimed in claim 1, wherein the OSV is a minimum value which is added such that when a size of the input data is converted to a binary value, a number of consecutive zero bits from the least significant bit (LSB) is at least one.

3. The device as claimed in claim 1, wherein the selection circuit generates a select signal for sequentially selecting the PN generators.

4. The device as claimed in claim 1, wherein the selection circuit generates a select signal for randomly selecting the PN generators.

5. The device as claimed in claim 1, wherein an initial state value of the PN generators is set to a state value satisfied by comparing a minimum weight determined by turbo encoding a predetermined input word for every case with a predetermined threshold value.

6. A device for generating L addresses, which are smaller in number than

$2^m \times N_g$ virtual addresses, for reading data from an interleaver memory in which L data bits are stored, the device comprising:

N_g PN generators each including m memories;

an address generator for adding an offset value to the input data size to provide a virtual address having a size of a multiple of 2^m , and generating addresses other than addresses corresponding to the offset value in address generation areas using the address generation areas having the size of 2^m ; and

means for reading the input data from the interleaver memory using the random addresses generated from the address generation areas.

7. The device as claimed in claim 6, wherein the address generator comprises: a selection circuit including said N_g PN (Pseudo Noise) generators, wherein one of the PN generators generates (OSV-1) offset values satisfying $OSV = 2^m \times N_g - L$ and $(2^m - OSV)$ non-zero states in response to a first clock signal and the other PN generators each generate $(2^m - 1)$ non-zero states, wherein the selection circuit selects the PN generators according to a predetermined order in response to a select signal and outputs a state generated from the selected PN generator;

means for detecting each offset state from one PN generator, providing said select signal for not selecting said one PN generator so that the detected offset state is not output, and generating high address bits related to each selection of the PN generators in response to clock pulses of a second clock signal having a shorter period than the first clock signal;

means for generating low address bits determined by subtracting one from each state output from the selection circuit when a number of selection periods of the PN generators is smaller than 2^m , and generating low address bits corresponding to $2^m - 1$ when the number of selection periods is 2^m ; and

an address buffer for storing the addresses, said L addresses each being comprised of the high address bits and the low address bits.

8. The device as claimed in claim 7, wherein the OSV is a minimum value which is added such that when a size of the input data is converted to a binary value, a number of consecutive zero bits from the least significant bit (LSB) is at least one.

9. The device as claimed in claim 7, wherein the selection circuit generates a select signal for sequentially selecting the PN generators.

10. The device as claimed in claim 7, wherein the selection circuit generates a select signal for randomly selecting the PN generators.

11. The device as claimed in claim 7, wherein an initial state value of the PN generators is set to a state value satisfied by comparing a minimum weight determined by turbo encoding a predetermined input word for every case with a predetermined threshold value.

12. A method for generating L addresses, which are smaller in number than $2^m \times N_g$ virtual addresses, for reading data from an interleaver memory in which L data bits are stored, the method comprising the steps of:

generating, in one of N_g PN generators, (OSV-1) offset values (OSV) satisfying $OSV = 2^m \times N_g - L$ and $(2^m - OSV)$ non-zero states;

generating, in each of the other PN generators, $(2^m - 1)$ non-zero states;

detecting each offset state from said one PN generator, and generating a select signal having a selection period for skipping selection of said one PN generator in a predetermined selection order for the PN generators so that the detected offset state is not selected;

selecting the PN generators according to the select signal and sequentially generating the non-zero states;

subtracting one from the non-zero states;

providing the subtracted states as low address bits when a number of the selection periods is smaller than 2^m , providing low address bits corresponding to $2^m - 1$ states when the number of the selection periods is 2^m , and generating high address bits associated with the select signal related to the low address bits; and

reading the L data bits from the interleaver memory using the addresses comprised of the low address bits and the high address bits.

13. The method as claimed in claim 12, wherein the OSV is a minimum value which is added such that when a size of the input data is converted to a binary value, a number of consecutive zero bits from the least significant bit (LSB) is at least one.

14. The method as claimed in claim 12, wherein said predetermined selection order is an order of sequentially selecting the PN generators.

15. The method as claimed in claim 12, wherein said predetermined selection order is an order of randomly selecting the PN generators.

16. The method as claimed in claim 12, wherein an initial state value of the PN generators is set to a state value satisfied by comparing a minimum weight determined by turbo encoding an predetermined input word for every case with a predetermined threshold value.

17. A method for interleaving input data having an input data size which is not a multiple of 2^m ($m > 1$), the method comprising the steps of:

sequentially storing the input data in a memory;

5 adding an offset value to the input data size to provide a virtual address size, which is a multiple (N_g) of 2^m ;

providing N_g address generation areas each having a size of 2^m , and generating addresses other than addresses corresponding to the offset value in the address generation areas; and

10 reading the input data from the memory using the addresses generated from the address generation areas.

18. The method as claimed in claim 17, wherein the address generating step comprises the steps of:

15 generating, in one of PN generators corresponding to the address generation areas, $(2^m - 1)$ non-zero states including offset states corresponding to the offset value (OSV);

generating, in each of the other PN generators, $(2^m - 1)$ non-zero states;

20 detecting each offset state from said one PN generator, and selecting the non-zero states from the PN generators according to a select signal having a selection period for skipping selection of said one PN generator in a predetermined selection order for the PN generators;

subtracting one from the selected states to provide the subtracted states as low address bits, and generating high address bits associated with the select signal related to the low address bits; and

25 generating the addresses comprised of the low address bits and the high address bits.

19. The method as claimed in claim 18, wherein the high address generating step comprises the steps of:

30 providing the subtracted states as the low address bits when a number of the selection periods is smaller than 2^m ;

providing the low address bits corresponding to $2^m - 1$ states when the number of the selection periods is 2^m ; and

generating the high address bits associated with the select signal related to the low address bits.

35 20. The method as claimed in claim 18, wherein the OSV is a minimum value which is added such that when a size of the input data is converted to a binary value, a number of consecutive zero bits from the least significant bit (LSB) is at least one.

21. The method as claimed in claim 18, said predetermined selection order is an order of sequentially selecting the PN generators.

5 22. The method as claimed in claim 18, wherein said predetermined selection order is an order of randomly selecting the PN generators.

10 23. The method as claimed in claim 18, wherein an initial state value of the PN generators is set to a state value satisfied by comparing a minimum weight determined by turbo encoding an predetermined input word for every case with a predetermined threshold value.

15 24. A turbo encoding device comprising:
a first component encoder for encoding input data having a size which is not a multiple of 2^m ($m>1$);
an interleaver for sequentially storing the input data in an interleaver memory, for adding an offset value to the input data size to provide a virtual address size, said virtual address size being a multiple (N_g) of 2^m , for providing N_g address generation areas each having a size of 2^m , for generating addresses other than addresses corresponding to the offset value in the address generation areas, and for reading the input data from the interleaver memory using the generated addresses; and
20 a second component encoder for encoding the data read from the interleaver memory.

1/14




FIG. 1




FIG. 2





FIG. 3



WRITE MODE: 0 1 2 3 4 5 6 7 8 $L-1$, L , $L+1$, $L+2$, $L+3$, $L+4$, $L+5$, $L+6$, $L+7$
READ MODE: 0 8 345

FIG. 4




FIG. 5




FIG. 6




FIG. 7




FIG. 8

9/14




FIG. 9




FIG. 10




FIG. 11




FIG. 12

13/14




FIG. 13




FIG. 14

INTERNATIONAL SEARCH REPORT

International application No.

PCT/KR00/00300

A. CLASSIFICATION OF SUBJECT MATTER**IPC7 H03M 13/27**

According to International Patent Classification (IPC) or to both national classification and IPC

B. FIELDS SEARCHED

Minimum documentation searched (classification system followed by classification symbols)

IPC 7 H03M G06F

Documentation searched other than minimum documentation to the extent that such documents are included in the fields searched

Korean Patents and applications for inventions since 1975

Korean Utility models and applications for Utility models since 1975

Electronic data base consulted during the international search (name of data base and, where practicable, search terms used)

C. DOCUMENTS CONSIDERED TO BE RELEVANT

Category*	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
A	WO 98 43168 A (INTERNATIONAL BUSINESS MACHINES CORPORATION) 1 October 1998 see column 2, line 5 - column 6, line 18 see column 7, line 15 - column 8, line 12 ; figures 1-3	1-24
A	US 5 333 289 A (HITACHI, LTD.) 26 July 1994 see column 6, line 45 - column 8, line 62 ; figures 1-5 see column 11, line 30 - column 12, line 63 ; figures 6-9 see column 5, line 20-63 see column 13, line 35-38	1-24
A	DAVID T. HARPER III ET AL : "CONFLICT-FREE VECTOR ACCESS USING A DYNAMIC STORAGE SCHEME" IEEE TRANSACTIONS ON COMPUTERS, vol. 40, no. 3 March 1991 pages 276-283	1-24



Further documents are listed in the continuation of Box C.



See patent family annex.

* Special categories of cited documents:

"A" document defining the general state of the art which is not considered to be of particular relevance

"E" earlier application or patent but published on or after the international filing date

"L" document which may throw doubts on priority claim(s) or which is cited to establish the publication date of citation or other special reason (as specified)

"O" document referring to an oral disclosure, use, exhibition or other means

"P" document published prior to the international filing date but later than the priority date claimed

"T" later document published after the international filing date or priority date and not in conflict with the application but cited to understand the principle or theory underlying the invention

"X" document of particular relevance: the claimed invention cannot be considered novel or cannot be considered to involve an inventive step when the document is taken alone

"Y" document of particular relevance: the claimed invention cannot be considered to involve an inventive step when the document is combined with one or more other such documents, such combination being obvious to a person skilled in the art

"&" document member of the same patent family

Date of the actual completion of the international search

19 JULY 2000 (19.07.2000)

Date of mailing of the international search report

19 JULY 2000 (19.07.2000)

Name and mailing address of the ISA/KR

Korean Industrial Property Office
Government Complex-Taejon, Dunsan-dong, So-ku, Taejon
Metropolitan City 302-701, Republic of Korea

Facsimile No. 82-42-472-7140

Authorized officer

NA. Yong Soo

Telephone No. 82-42-481-5680



INTERNATIONAL SEARCH REPORT

international application No.

PCT/KR00/00300

C (Continuation). DOCUMENTS CONSIDERED TO BE RELEVANT

Category*	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
A	KIN-MAN LAM ET AL : " A NEW STORAGE SCHEME FOR CONFLICT-FREE VECTOR ACCESS" COMPUTER, COMMUNICATION, CONTROL AND POWER ENGINEERING PROCEEDINGS, IEEE TENCON '93., 1993 vol. 1, pages 32-35	1-24

INTERNATIONAL SEARCH REPORT

Information on patent family members

International application No.

PCT/KR00/00300

Patent document
cited in search report

Publication
date

Patent family
member(s)

Publication
date

US 5333289

26-07-94

JP 4030231 A

03-02-92